CIRCULATION	Suffix	Amendt.	
C.B.S. No.1 & MAG.	B	SUPERSESSION NOTE ADDED. DIAGRAM MADE YELLOW.	25.11.63.
	A	REDRAWN. NOTES REVISED	4-4-56

PAPER: Y

MAGNETO AND C.B.S. No.1 SYSTEMS

SHARED SERVICE (MANUAL)

SUBSCRIBER'S EXTENSION PLAN 1B (INTERNAL ONLY)

N4043
2-2-51

NOTES

1. FOR THE X INSTALLATION USE DIAGRAM N4066 WITHOUT MODIFICATION
2. FOR THE Y INSTALLATION USE DIAGRAM N4066 BUT CONNECT THE A LINE TO BT2 AND THE B LINE TO BT1. THE COILS OF ANY MAGNETO BELLS IN CIRCUIT SHOULD BE CONNECTED IN SERIES.
   IN ADDITION FIT A CAPACITOR IN THE EARTH LEAD AT THE MAIN STATION AS FOLLOWS:-
   USING TELEPHONE No.1/196LB & BELL SET No.21 OR 31.
   (a) TRANSFER EARTH CONNEXION FROM BT3 TO BT8.
   (b) CONNECT CAPACITOR MC No. 102 1/1 TO BT3 & BT8.
   USING TELEPHONE No. 396 LB
   FIT CAPACITOR PAPER No. 7712. THIS IS HELD IN PLACE BY A CLIP No. 56 3/4 IN. WHICH IS FIXED UNDER ONE OF THE BELL FIXING SCREWS.
   WHERE AN EXTN. BELL IS REQD. A BELL No. 64D SHOULD BE FITTED BETWEEN BT4 & BT5.
3. WHERE A MAGNETO EXCHANGE IS MODIFIED TO DGM. CBS 1124 AT THE X STATION.
   USING TELEPHONE No. 1/196LB—STRAP T8 & T9 AT MAIN & EXTN. TELEPHONES.
   USING TELEPHONES Nos 392LB & 396LB—CONNECT T7 TO T11 INSTEAD OF TO T8 AT MAIN & EXTN. TELEPHONES.
4. PLAN 1A SHOULD BE PROVIDED FOR NEW WORK.